FieldLink process networking
AS-Interface

# Power supplies

# Model number PS459004A

## 8.0 amp AS-Interface power supply

This compact power supply is designed for use with AS-Interface systems where power and data share the same wires. The 8.0 amp power supply provides power to the AS-Interface bus for operation of masters and slaves for output devices. Integrated into the supply is a power conditioner which decouples data from the power supply enabling signal and power to be carried on the same pair of wires.

#### Features

- Current limited/short circuit protected
- Regulated to ± 3%

 Power decoupled from communication signal







Specifications	
Output voltage	30.55 VDC ± 3%
Output current	8.0 amps (244 watts)
Output inductance	100 mH ± 10 %
Input voltage	Selectable 120 / 240 VAC (47-63 Hz)
Displays	Power on, green LED
Current limits	8.4 amp (min)
Operating temperature	$-10^{\rm o}$ to $+70^{\rm o}$ C (+14° to +158°F)
Storage temperature	-25° to +85°C (-13° to +185°F)
Housing	Al/Mg alloy, DIN rail mounting
Dimensions (L, W, H)	124mm, 91mm, 112mm
Ingress protection	IP20, field enclosure required
Weight	890g (2.0 pounds)



# Schematic drawing



32 valmet.com/flowcontrol



Valmet's professionals around the world work close to our customers and are committed to moving our customers' performance forward – every day.

### Valmet Flow Control Oy

Vanha Porvoontie 229 01380 Vantaa, Finland flowcontrol@valmet.com +358 10 417 5000 valmet.com/flowcontrol

### Valmet Flow Control Inc. Stonel product center

26271 US Hwy 59, Fergus Falls, MN 56537 USA. Tel. +1 218 739 5774. sales.stonel@valmet.com valmet.com/flowcontrol



